

LS 6500-E



LS 6500-E ATS

Avviamento automatico in caso di black out



Standard version



Optionals version



Accessorio - Accessorie



GENERATORE A BENZINA - 4 TEMPI

Gruppo elettrogeno monofase con motore a scoppio 4 tempi a benzina, flangiato ad un alternatore a 2 poli monofase. Sistema di regolazione brushless a condensatore.

Avviamento con autoavvolgente ed elettrico a batteria.

Quadro di comando con 2 prese monofase CEE 16A e 2 protettori termici.

Optional: pannello prese con 1 presa monofase CEE 32A, 1 presa monofase CEE 16A e 2 protettori termici.

GASOLINE ENGINE GENERATOR - 4 STROKE

Single phase generating set with 4-stroke gasoline engine coupled to single phase 2-pole alternator.


System brushless with capacitor regulation.

Recoil or electric starter with battery.


Control panel with 2 single phase CEE plugs 16A and 2 termic protectors.

Optionals: control panel with 1 single phase CEE plug 32A, 1 single phase CEE plug 16A and 2 termic protectors.

MOTORE - ENGINE

Modello Model	Potenza motore Motor power	Avviamento Start system	Cilindrata Displacement	Carburante Fuel	Capacità serbatoio Tank Capacity	Rumorosità Noise db(A)	Servizio continuo orario Continuous duty running time
type	Hp / 3600 r.p.m.	type	cc	type	lt	LpA a 7m LwA	h
Monocilindrico, raffreddamento ad aria, 4 - tempi Single cylinder, forced air cooling, 4 - stroke	13 (G 390)	manuale - elettrico recoil - electric	389	Benzina Gasoline	6,5	70  97	2,5

GENERATORE - GENERATOR

Modello Model	Frequenza Frequency	Tensione Voltage	Potenza uso continuo Continuous duty power	Potenza max. Max. power	Dimensioni Dimensions	Peso Weight
	Hz.	V	kVA	kVA	mm	Kg
	50	230	6	6,5	750 x 595 x 600	89